

# Syncbox Specsheet

## Syncbox

The Syncbox is a compact computer, designed by Guide ID to charge and synchronize Podcatcher audio guides. You can connect up to 10 dockingstations (100 Podcatchers) to one Syncbox. If you have more Podcatchers on location you will need multiple Syncboxes.

## Specifications

### Operating System

Linux

### Power

85-250 VAC, 275 W, 1.2 A @ 230V  
(EU C14 connector) (01)

### Connection

Integrated LAN 100 MBit (RJ-45) (02)

### USB ports

Front: USB 2.0 (type A) (03)

Back: 10 x USB 2.0 (type A) (07)

### Start/Shutdown button (05)

To power the syncbox on or off

### LED indicators

4 dual-color LED indicators (06)

### More info on:

<https://help.guideid.com/kb/syncbox/>

## Physical characteristics

### Dimensions

185x 60x 140 mm (W x H x D)

7.28x 2.36 x 5.51" (W x H x D)

### Weight

753 gr. / 26,56 oz

## Product Details

Certifications	CE, FCC
Types of user	Ordinary person
Supply type	AC mains
Supply voltage tolerancerance	85 - 250 VAC
Class	I
Considered rating and location of main protective device	1.9A/115VAC, 1.2A/230VAC, in equipment
Supply system	TT
Mobility	Stationary
Operating duration	Continuous
Over voltage category	III
Pollution degree	PD2
Restricted access location	No
Rated maximum ambient operating temperature	50 °C
IP rating	-
Maximum altitude	2000 m
Mass	775 g
CE Emission class	Residential (EN 55032: B) Household appliances (61000-3-2: A)
FCC Emission class	Residential (47 CFR 15: B)

